


Wi-Fi

Smart Multipurpose Sensor

INSTRUCTION



Thanks for purchasing our products,
please read this instruction before using

Main Function:

- PIR detects human body or animals that are moving
- Detect open/close status of the door/window

Specifications:

- Power Supply: 3pcs AAA 1.5V Battery
- Standby Time: 5~7 months (trigger 20 times/day)
- Sensitivity Distance: 5~7m
- Detection angle : 100°
- Wireless Type: 2.4Ghz WiFi
- Protocol: IEEE802.11 b/g/n
- Main Body's Size: 90*40*17mm
- Deputy Body's Size: 33*10*12mm

Download App

1. Android Smart Phone: download "Smart Life" from GooglePlay.
2. IOS iphone: download "Smart Life" from App Store.



Run App

1. Run "Smart Life" from your smart phone desktop.
2. Register and login



Note: Open the phone settings to ensure smart life app notifications permission is turned on.

Connect the Multipurpose Sensor to Smart Life app

1. Open the back cover and remove the battery insulation pull tab. Hold the device "Reset" button for 5 seconds until the indicator light will flash quickly.



IMPORTANT: Make sure your smartphone is connected to your home 2.4Ghz Wi-Fi signal before the following setup. Turn on your smartphone's Bluetooth.

2. Launch the app and tap the Plus (+) in the top right corner to add device.



3. Enter your home Wi-Fi name and password, then tap Confirm.




4. Now your sensor is successfully added to Smart Life app. Tap Done.



5. Click on the set icon and open the App Push



6. Turn the smart sensor over for the motion sensor facing up, and wave your hand in front of the motion sensor.



Installation:

Double-sided tape and screws are included in the package, you can use the included screws or double-sided tape to install the smart door sensor on the door or window.

NOTE: the height of the smart sensor should keep over 60 inches

